

Infrared Thermometer

Non-Contact | Accurate | Convenient

The Guardian of Every Family's Health





Infrared Thermometer BITEWJ-02


One Button Temperature



Measurement



Sensitive Probe



Calibration



Test Tip



Fever Tip

Product Description-- BITEWJ-02

1. High precision infrared sensor, stable and reliable performance
2. Strong environment temperature adaptability, which normally works well under special circumstances
3. Automatically save the last 10 measurements
4. Large LCD screen, high brightness backlight, display clear and soft.
5. Abnormal reminding



Product Operation -- BITEWJ-02

1. Aim the body thermometer probe at the center of the forehead and keep it perpendicular about 3-4cm away. Press the Measure key which will show the measured value.
2. If the measured value is higher than the temperature alarm point, it will send alarm sound.



3-4cm



Product Description -- BITEWJ-02

1. Infrared Sensor
2. Switch and Measure Key
3. Temperature -
4. Set Key
5. Temperature +
6. LCD Display
7. Battery Cover



Product Parameters -- BITEWJ-02

1. Product Name: Infrared Thermometer
2. Model Number: BITEWJ 02
3. Measuring Distance: 3cm-4cm
4. Measuring Range: 32.5°C ~ 42.5°C
5. Max Allowable Error:
 - ±0.2°C (35.0°C-41.0°C);
 - ±0.3°C (32.5°C-34.9°C & 41.1°C-42.9°C)
6. Display Resolution: 0.1°C
7. Operating Environment: 16°C ~ 38°C
Humidity ≤ 85%
8. Size: 153mm × 104mm × 42mm
9. Storage Environment: -20°C ~ +55°C
Humidity: ≤ 93%
10. Power Supply: DC.3V (2pcs of AA Batteries)
11. Indicator:
 - 1) It will show ERR if the operating temperature is lower than 16°C or higher than 38°C
 - 2) It will show Li if the body temperature is lower than 32.0°C ± 0.3°C and will show Hi if it's higher than 42.9°C ± 0.3°C
 - 3) Low Battery Indicator
12. Automatic shutdown time 12s



Infrared Thermometer

QUICK TEMPERATURE MEASURE

